

JUN 08 2009

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

Listing and Amendments to the Claims

This listing of claims will replace all prior versions, and listings, of claims in the application:

1. (Presently presented) A fault-tolerant router, comprising:

a first router matrix card, said first router matrix card receiving N parity encoded input digital audio data streams and generating, from said N parity encoded input digital audio data streams, a first set of M parity encoded output digital audio streams, wherein M and N are integers and M is different from N;

a second router matrix card, said second router matrix card receiving said N parity encoded input digital audio data streams and generating, from said N parity encoded input digital audio data streams, a second set of M parity encoded digital audio streams;

an output card coupled to said first router matrix card and said second router matrix card, said output card receiving said first set of M parity encoded output digital audio streams from said first router matrix card and said second set of said M parity encoded output digital audio streams from said second router matrix card, providing, as an output therefrom, a selected one of said first and second sets of M parity encoded output digital audio streams, and switching from said selected one of said first and second sets of M parity encoded output digital audio data streams to an unselected one of said first and second sets of M parity encoded output digital audio data streams based upon detecting a parity error in said selected one of said first and second sets of M parity encoded output digital audio data streams regardless of whether a parity error is present in said unselected one of said first and second sets of M parity encoded output digital audio data streams.

2. (Previously Presented) The apparatus of claim 1, wherein said output card further comprises a switching circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card and said second set of M parity encoded output digital audio data streams from said second router matrix card, said switching circuit switching from said selected one of said first and second sets of M parity encoded output digital audio data

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

streams to said unselected one of said first and second sets of M parity encoded output digital audio data streams in response to assertion of a switching signal.

3. (Previously Presented) The apparatus of claim 2, wherein said output card further comprises:

a first parity check circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card;

a second parity check circuit coupled to receive said second set of M parity encoded output digital audio data streams from said second router matrix card; and

a logic circuit coupled to receive a first parity error signal from said first parity check circuit and a second parity check error signal from said second parity check circuit, said logic circuit determining, based upon said first parity error signal received from said first parity check circuit and said second parity error signal received from said second parity check circuit, whether to assert said switching signal.

4. (Previously Presented) The apparatus of claim 3, wherein said output card further comprises

a first delay circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card; and

a second delay circuit coupled to receive said second set of M parity encoded output digital audio data streams from said second router matrix card;

said switching circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card and said second set of M parity encoded output digital audio data streams from said second router matrix card via said first delay circuit and said second delay circuit, respectively.

5. (Previously presented) The apparatus of claim 3, wherein said logic circuit asserts said switching signal based upon detection of said parity error in said selected one of said first and second sets of M parity encoded output digital audio data streams.

6. (Cancelled)

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

7. (Previously Presented) The apparatus of claim 3, wherein said switching circuit switches back from said unselected one of said first and second sets of M parity encoded output digital audio data streams to said selected one of said first and second sets of M parity encoded output digital audio data streams based upon assertion of said switching signal.

8. (Previously Presented) The apparatus of claim 7, wherein said logic circuit asserts said switching signal based upon detection of a parity error in said unselected one of said first and second sets of M parity encoded output digital audio data streams.

9. (Previously Presented) The apparatus of claim 7, wherein said logic circuit asserts said switching signal based upon detection of a parity error in said unselected one of said first and second sets of M parity encoded output digital audio data streams only if no parity error is present in said selected one of said first and second sets of M parity encoded output digital audio streams.

10. (Previously Presented) The apparatus of claim 7, wherein said logic circuit asserts said switching signal based upon detection of a parity error in said unselected one of said first and second sets of M parity encoded output digital audio data streams regardless of whether a parity error is present in said selected one of said first and second sets of M parity encoded output digital audio data streams.

11. (Currently amended) For a broadcast router having an input card, a first router matrix card and a second router matrix card, said input card transmitting a set of N input digital audio data streams to said first router matrix card and said second router matrix card, said first router matrix card outputting a first set of M output digital audio data streams and said second router matrix outputting a second, replicated, set of M output digital audio data streams, a method of selecting one of said first and second sets of M output digital audio data streams as the output of said broadcast router, wherein M and N are integers and M is different from N, the method comprising:

propagating said first set of M output digital audio data streams through at least one components of said first router matrix card;

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

~~each one of said at least one component of said first router matrix card adding at least one bit of information to said first set of M output digital audio data streams propagating therethrough;~~

modifying at least one bit of information in said first set of M output digital audio data streams propagating through at least one component assigned to the one information bit upon the component detecting the presence of one of an error or fault condition;

propagating said second set of M output digital audio data streams through at least one component of said second router matrix card;

~~each one of said at least one component of said second router matrix card adding at least one bit of information to said second set of M output digital audio data streams propagating therethrough;~~

modifying at least one bit of information in said second set of M output digital audio data streams propagating through at least one component assigned to the one information bit upon the component detecting the presence of one of an error or fault condition; and

selecting one of said first and second sets of M output digital audio data streams as the output of said broadcast router based upon a comparison of said at least one bit of information added to said first set of M output digital audio data streams to said at least one bit of information added to in said second set of M output digital audio data streams.

12. (Previously Presented) The method of claim 11, wherein said at least one bit of information is comprised of at least one status bit.

13. (Previously Presented) The method of claim 11, wherein said at least one bit of information is comprised of at least one health bit.

14. (Previously Presented) The method of claim 13, wherein selecting one of said first and second sets of M output digital audio data streams as the output of said broadcast router further comprises:

determining a first sum by adding said at least one bit added to said first set of M output digital audio data streams;

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

determining a second sum by adding said at least one bit added to said second set of M output digital audio data streams; and

selecting one of said first and second sets of N output digital audio data streams as the output of said broadcast router based upon a comparison of said first sum to said second sum.

15. (Previously Presented) The method of claim 11, and further comprising:

encoding parity information into said first set of N input digital audio data streams prior to transmission of said input digital audio data streams to said first router matrix of said first router card and said second router matrix of said second router matrix card, said first set of M output digital audio data streams output said first router matrix being a first set of M parity encoded digital audio data streams and said second set of M output digital audio data streams output said second router matrix being a second set of M parity encoded digital audio data streams;

checking said first and second sets of M parity encoded output digital audio data streams for parity errors;

selecting one of said first and second sets M parity encoded output digital audio data streams as the output of said broadcast router based upon the presence of parity errors in said first set of N output digital audio data streams, the presence of parity errors in said second set of N output digital audio data streams and said comparison of said at least one bit of information added to said first set of M parity encoded output digital audio data streams to said at least one bit of information added to said second set of M parity encoded output digital audio data streams.

16. (Previously Presented) The method of claim 15, wherein selecting one of said first and second sets of M parity encoded output digital audio data streams as the output of said broadcast router further comprises:

determining a first sum by adding said at least one bit added to said first set of M parity encoded output digital audio data streams;

determining a second sum by adding said at least one bit to said second set of M parity encoded output digital audio data streams; and

selecting, one of said first and second sets of M parity encoded output digital audio data streams as the output of said broadcast router based upon the presence of parity errors in said first

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

set of M parity encoded output digital audio data streams, the presence of parity errors in said second set of M parity encoded output digital audio data streams and a comparison of said first sum to said second sum.

17. (Previously Presented) The apparatus of claim 1, wherein said output card is further configured to continue providing as the output therefrom the unselected one of said first and second sets of M parity encoded output digital audio streams, even if no further parity error is detected in said selected one of said first and second sets, unless a parity error is detected in said unselected one of said first and second sets.

18. (Previously presented) A fault-tolerant router, comprising:

a first router matrix card, said first router matrix card receiving N parity encoded input digital data streams and generating, from said N parity encoded input digital data streams, a first set of M parity encoded output digital streams, wherein M and N are integers and M is different from N;

a second router matrix card, said second router matrix card receiving said N parity encoded input digital data streams and generating, from said N parity encoded input digital data streams, a second set of M parity encoded digital streams;

an output card coupled to said first router matrix card and said second router matrix card, said output card receiving said first set of M parity encoded output digital streams from said first router matrix card and said second set of said M parity encoded output digital streams from said second router matrix card, providing, as an output therefrom, a selected one of said first and second sets of M parity encoded output digital streams, and switching from said selected one of said first and second sets of M parity encoded output digital data streams to an unselected one of said first and second sets of M parity encoded output digital data streams based upon detecting a parity error in said selected one of said first and second sets of M parity encoded output digital data streams regardless of whether a parity error is present in said unselected one of said first and second sets of M parity encoded output digital audio data streams.

19. (Currently amended) For a broadcast router having an input card, a first router matrix card and a second router matrix card, said input card transmitting a set of N input digital data streams

Ser. No.: 10/518,670
 Amendment dated May 29, 2009
 Reply to Office Action of April 1, 2009

PATENT
 PU020289
 CUSTOMER NO.: 24498

to said first router matrix card and said second router matrix card, said first router matrix card outputting a first set of M output digital data streams and said second router matrix outputting a second, replicated, set of M output digital data streams, a method of selecting one of said first and second sets of M output digital data streams as the output of said broadcast router, wherein M and N are integers and M is different from N, the method comprising:

propagating said first set of M output digital data streams through at least one components of said first router matrix card;

~~each one of said at least one component of said first router matrix card adding at least one bit of information to said first set of M output digital data streams propagating therethrough;~~

modifying at least one bit of information in said first set of M output digital audio data streams propagating through at least one component in said first router matrix card assigned to the one information bit upon the component detecting the presence of one of an error or fault condition.

propagating said second set of M output digital data streams through at least one component of said second router matrix card;

~~each one of said at least one component of said second router matrix card adding at least one bit of information to said second set of M output digital data streams propagating therethrough; and~~

modifying at least one bit of information in said second set of M output digital audio data streams propagating through at least one component in said second router matrix card assigned to the one information bit upon the component detecting the presence of one of an error or fault condition.

selecting one of said first and second sets of M output digital data streams as the output of said broadcast router based upon a comparison of said at least one bit of information added to in said first set of M output digital data streams to said at least one bit of information added to in said second set of M output digital data streams.

20. (Previously Presented) A fault-tolerant router, comprising:

a first router matrix card, said first router matrix card receiving N parity encoded input digital audio data streams and generating, from said N parity encoded input digital audio data streams, a first set of M parity encoded output digital audio streams;

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

a second router matrix card, said second router matrix card receiving said N parity encoded input digital audio data streams and generating, from said N parity encoded input digital audio data streams, a second set of M parity encoded digital audio streams; and

an output card coupled to said first router matrix card and said second router matrix card, said output card receiving said first set of M parity encoded output digital audio streams from said first router matrix card and said second set of said M parity encoded output digital audio streams from said second router matrix card, providing, as an output therefrom, a selected one of said first and second sets of M parity encoded output digital audio streams, and switching from said selected one of said first and second sets of M parity encoded output digital audio data streams to an unselected one of said first and second sets of M parity encoded output digital audio data streams based upon detecting a parity error in said selected one of said first and second sets of M parity encoded output digital audio data streams,

wherein said output card further comprises:

a switching circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card and said second set of M parity encoded output digital audio data streams from said second router matrix card, said switching circuit switching from said selected one of said first and second sets of M parity encoded output digital audio data streams to said unselected one of said first and second sets of M parity encoded output digital audio data streams in response to assertion of a switching signal;

a first parity check circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card;

a second parity check circuit coupled to receive said second set of M parity encoded output digital audio data streams from said second router matrix card; and

a logic circuit coupled to receive a first parity error signal from said first parity check circuit and a second parity check error signal from said second parity check circuit, said logic circuit determining, based upon said first parity error signal received from said first parity check circuit and said second parity error signal received from said second parity check circuit, whether to assert said switching signal, and

wherein said logic circuit asserts said switching signal based upon detection of said parity error in said selected one of said first and second sets of M parity encoded output digital audio

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

data streams regardless of whether a parity error is present in said unselected one of said first and second sets of M parity encoded output digital audio data streams.

21. (Previously Presented) A fault-tolerant router, comprising:

a first router matrix card, said first router matrix card receiving N parity encoded input digital audio data streams and generating, from said N parity encoded input digital audio data streams, a first set of M parity encoded output digital audio streams;

a second router matrix card, said second router matrix card receiving said N parity encoded input digital audio data streams and generating, from said N parity encoded input digital audio data streams, a second set of M parity encoded digital audio streams; and

an output card coupled to said first router matrix card and said second router matrix card, said output card receiving said first set of M parity encoded output digital audio streams from said first router matrix card and said second set of said M parity encoded output digital audio streams from said second router matrix card, providing, as an output therefrom, a selected one of said first and second sets of M parity encoded output digital audio streams, and switching from said selected one of said first and second sets of M parity encoded output digital audio data streams to an unselected one of said first and second sets of M parity encoded output digital audio data streams based upon detecting a parity error in said selected one of said first and second sets of M parity encoded output digital audio data streams,

wherein said output card further comprises:

a switching circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card and said second set of M parity encoded output digital audio data streams from said second router matrix card, said switching circuit switching from said selected one of said first and second sets of M parity encoded output digital audio data streams to said unselected one of said first and second sets of M parity encoded output digital audio data streams in response to assertion of a switching signal;

a first parity check circuit coupled to receive said first set of M parity encoded output digital audio data streams from said first router matrix card;

a second parity check circuit coupled to receive said second set of M parity encoded output digital audio data streams from said second router matrix card; and

Ser. No.: 10/518,670
Amendment dated May 29, 2009
Reply to Office Action of April 1, 2009

PATENT
PU020289
CUSTOMER NO.: 24498

a logic circuit coupled to receive a first parity error signal from said first parity check circuit and a second parity check error signal from said second parity check circuit, said logic circuit determining, based upon said first parity error signal received from said first parity check circuit and said second parity error signal received from said second parity check circuit, whether to assert said switching signal, and

wherein:

said switching circuit switches back from said unselected one of said first and second sets of M parity encoded output digital audio data streams to said selected one of said first and second sets of M parity encoded output digital audio data streams based upon assertion of said switching signal, and

said logic circuit asserts said switching signal based upon detection of a parity error in said unselected one of said first and second sets of M parity encoded output digital audio data streams regardless of whether a parity error is present in said selected one of said first and second sets of M parity encoded output digital audio data streams.